

## Connector installation instruction for 1-1/4" leaky RF cable

Series	N	7/16
Suitable connector type	NM 1 1/4" R NF 1 1/4" R	7/16M-1-1/4"R 7/16F -1-1/4"R



1. Peel the leaky cable mark line at least 60mm.



2. Using special knife resects superfluous length of the cable.



3. The surface should be plane and clean.



4. Cut around the jacket of the cable 8-9mm, use the diagonal pliers strip the jacket of the cable.



5. Fix back DOS Shell and cable clamp on cable.



6. Evenly flaring the cable copper skin on the cable clamp.



7. Fix front DOS Shell on cable.



8. Keep main shell body stopped, turn back DOS shell to tighten main shell body.



9. Assembling is finished.